

Simplifica las siguientes tablas de Karnaugh:

1)

C \ AB	00	01	11	10
0	1	1		
1			1	1

2)

C \ AB	00	01	11	10
0	1	1		1
1	1		1	1

3)

C \ AB	00	01	11	10
0	1	1		1
1		1	1	

4)

C \ AB	00	01	11	10
0	1	1		
1	1	1	1	

5)

C \ AB	00	01	11	10
0	1	1		
1	1	1	1	1

6)

CD \ AB	00	01	11	10
00				1
01		1	1	
11		1	1	
10	1	1	1	1

7)

CD \ AB	00	01	11	10
00	1	1		1
01				1
11			1	1
10			1	1

8)

CD \ AB	00	01	11	10
00	1	1		1
01	1	1		
11	1	1	1	1
10	1	1	1	1

9)

CD \ AB	00	01	11	10
00	1			1
01		1	1	
11		1	1	
10		1	1	

10)

CD \ AB	00	01	11	10
00	1			1
01		1	1	
11		1		1
10	1	1		1

11)

CD \ AB	00	01	11	10
00		1		
01	1		1	1
11	1			1
10			1	1

12)

C \ AB	00	01	11	10
0		1		1
1	1		1	1